

<u>Type</u>	<u>Value</u>	<u>WC2700</u>	<u>X</u>	<u>WC2700 Ref Des</u>
Bracket 4-40	<b>Tap 1 side</b>	2	<input type="checkbox"/>	
Cable Power 20 Ga 18"	<b>4X red,blk,blk,wht</b>	1	<input type="checkbox"/>	
Cap ceramic NPO	<b>150 pF "151"</b>	1	<input type="checkbox"/>	C4
Cap ceramic NPO	<b>22 pF "22"</b>	1	<input type="checkbox"/>	C1
Cap ceramic X7R	<b>.01 uF "103"</b>	1	<input type="checkbox"/>	3
Cap ceramic Z5U	<b>0.1 uF "104" (Axial)</b>	3	<input type="checkbox"/>	2, 7, 8
Cap electrolytic	<b>100 uF</b>	2	<input type="checkbox"/>	6, 9
Cap mylar	<b>0.1 uF "104"</b>	1	<input type="checkbox"/>	5
Connector .156	<b>M header 4 pin</b>	1	<input type="checkbox"/>	J10
Diode 1A 50V	<b>1N4001</b>	2	<input type="checkbox"/>	D6, 7
Diode signal	<b>1N4148 DO35</b>	4	<input type="checkbox"/>	1, 2, 3, 5
IC 4050	<b>Hex Buffer non-inv</b>	1	<input type="checkbox"/>	U3
IC LM4040AIZ-5.0	<b>Reference 5V 0.1%</b>	1	<input type="checkbox"/>	D4
IC MAX362	<b>Quad Analog SW NO</b>	1	<input type="checkbox"/>	U5, Substitute for MAX365
IC TL074	<b>Quad FET op amp</b>	3	<input type="checkbox"/>	U1, 2, 4
Jack, stereo pcb	<b>3.5 mm</b>	9	<input type="checkbox"/>	
Knob (color) 16mm	<b>6mm Push On</b>	3	<input type="checkbox"/>	
LED T1	<b>Blue</b>	1	<input type="checkbox"/>	LED2
LED T1	<b>Green</b>	1	<input type="checkbox"/>	LED1
Manual	<b>WC2700</b>	1	<input type="checkbox"/>	
Nut Kep	<b>4-40 SS</b>	2	<input type="checkbox"/>	
PCB	<b>WC2700 (2 part)</b>	1	<input type="checkbox"/>	
Pot 9mm PCB	<b>50K lin bshg</b>	2	<input type="checkbox"/>	R2, 3
Pot 9mm PCB	<b>50K lin, plain</b>	1	<input type="checkbox"/>	R1
PTC MF-R010	<b>100mA</b>	2	<input type="checkbox"/>	PS1, 2
Res 1/4W 5% CF	<b>100</b>	1	<input type="checkbox"/>	R24
Res 1/4W 5% CF	<b>100K</b>	8	<input type="checkbox"/>	7, 10, 16, 17, 18, 19, 20, 26,
Res 1/4W 5% CF	<b>10K</b>	3	<input type="checkbox"/>	6, 9, 25
Res 1/4W 5% CF	<b>1K</b>	4	<input type="checkbox"/>	13, 14, 15, 23
Res 1/4W 5% CF	<b>1M</b>	2	<input type="checkbox"/>	4, 21
Res 1/4W 5% CF	<b>220K</b>	1	<input type="checkbox"/>	8
Res 1/4W 5% CF	<b>2K</b>	1	<input type="checkbox"/>	12
Res 1/4W 5% CF	<b>33</b>	1	<input type="checkbox"/>	22
Res 1/4W 5% CF	<b>47K</b>	1	<input type="checkbox"/>	5
Res 1/4W 5% CF	<b>5.6K</b>	1	<input type="checkbox"/>	11
Res Net CF "10B104"	<b>100K 5x sep. 10 pin</b>	1	<input type="checkbox"/>	RN2
Res Net CF "6A104"	<b>100K 5x com. 6 pin</b>	1	<input type="checkbox"/>	1
Res Net CF "8B563"	<b>56K 4x sep. 8 pin</b>	1	<input type="checkbox"/>	3
Screw MS 4-40	<b>1/4" Phil Pan SS</b>	2	<input type="checkbox"/>	Bracket mounting to PCB
Screw MS 4-40 Black	<b>1/4" Phil Pan SS</b>	2	<input type="checkbox"/>	Bracket mounting to front panel
Screw ST SS Philips	<b>#4 x 1/4</b>	2	<input type="checkbox"/>	Module mounting to Rack
Socket IC	<b>14 pin</b>	3	<input type="checkbox"/>	
Socket IC	<b>16 pin</b>	2	<input type="checkbox"/>	
Transistor NPN	<b>2N3904</b>	2	<input type="checkbox"/>	Q1, 2
Wire, misc colors:	<b>24/7 GA stranded</b>	3	<input type="checkbox"/>	